


Project	
Туре	
Notes	

#### PERFORMANCE PER LINEAR FOOT AT 3500K

NOMINAL LUMEN OUTPUT	INPUT WATTS*	EFFICACY	SHIELDING
1000 lm/ft	9.9 W/ft	97 lm/W	L

Please consult factory for custom lumen output and wattage.









## **Ordering Guide**

B2SQDLED		B2SQDLED								
PRODUCT ID		NOM. LUMENS/FT			CRI		COLOR TEMP.		SHIELDING	
B2SQDLED	Pendant Direct LED	400	400 lm/ft	80	80 CRI	27	2700 K	so	spotless lens	
		500	500 lm/ft	90	90 CRI	30	3000 K	L	louver (1)	
		750	750 lm/ft			35	3500 K	0.25G	0.25" Glo lens	
		1000	1000 lm/ft *			40	4000 K			
			listed min and max are available. or outputs outside of the listed range.						available with direct and 4' combinations; otherwise consult factory.	

LENGTH		GTH MR (OPTIONAL)		FINISH		VOLTAGE		DRIVER		CIRCUITS	
2	2'	M11LED(#)	MR 11 LED	AP	aluminum paint	120	120 V	<b>DP</b> dimming (0-10V) 1%		1	1 circuit
3	3'			w	white	277	277 V	<b>D</b> dimming (0-10V) 5% 347V standard (3)		2	2 circuits
4	4'			BLK	black	347	347 V (2)	(2) LT Lutron (4)		+E(#)	emergency circuit (6)
5	5'			С	custom	UNV	universal	ersal <b>BI</b> bi-level dimming		+NL(#)	night light circuit (6)
6	6′						O other (5)		+GTD(#)	generator transfer device (6)	
8	8'									+M	MR
12	12'										
S#	system run										
		Add 9" per lamp. Separate circuits in Requires 120V or 2	ncluded			(2) D dimmin standard	g (0-10V) 5%	(4) Sp	r 347 V only ecify system ase consult factory; see page 2	(6) Specify quan	tity

N	MOUNTING/SUSPENSION		BATTERY (OPTIONAL)		OTHER (OPTIONAL)		IC CONTROLS (OPTIONAL)		CUSTOM (OPTIONAL)	
CA(#)	drywall+cable length (36" std.)	B#	battery pack (integral)	F	fuse	DS#	daylight sensor	С	custom	
CT9(#)	TB/TG 9/16+cable length (36" std.)					OS#	occupancy sensor			
CT15(#)	TB/TG15/16+cable length (36" std.)					DOS#	daylight & occupancy sensor			
CTS(#)	ST+cable length (36" std.)					EN#	Enlighted integral (7)			
SA(#)	drywall+stem length >48" (18" std.)					ENR#	Enlighted remote (7)			
White canopy standard			es 120V or 277V um 4ft; please consult factory	Requi	res 120V or 277V		nsult factory tity. Requires 8" blank 6 for more details	Please	specify	



#### SPECIFICATIONS

#### CONSTRUCTION

Extruded aluminum (0.075" nominal) Housing

Up to 70% recycled content

**End Cap** Cast aluminum

**Interior Brackets** Die formed sheet steel (20 gauge)

Reflectors White powder coated sheet steel (22 gauge) Die formed semi-specular aluminum (22 gauge) Louvers

Extruded acrylic (0.070" nominal) Lenses

Die formed sheet steel (16 gauge) Hanger Suspension Aircraft cable or Ø 1/2" stem Cable Grips Quick connecting / release

#### ELECTRICAL

L3D - Hi-Lume A-Series EcoSystem 3-Wire Control (1%) Lutron driver

LDE1 - EcoSystem H-Series (1%)

LDE5 - EcoSystem 5-Series (5%)

LTE - Hi-Lume® A-series 2Wires Forward Phase (1%)

Other drivers DALI - Digital Addressable Lighting Interface

DMX - Digital Multiplex

LV - line voltage - Advance Mark 10 Xitanium SR - For wireless sensor

**Emergency** Integral emergency battery pack or emergency circuit

optional.

Input Voltage 120V, 277V, 347V, UNV.

f Incorporating these components may have limitations or affect the length of the luminaire. Please contact factory for more details.

#### LED SYSTEM

**CRI** Minimum 80 or 90 color rendering index.

**CCT** Choice of 2700K, 3000K, 3500K and 4000K color

> temperature with a great color consistency (within 3-step MacAdam ellipse). Both within

fixture and fixture to fixture.

**LED life** Minimum 50,000h with 85% of lumen

> maintenance in 25°C ambient temperature, in compliance with IES LM-80 testing

measurements.

**Thermal** Aluminum housing acting as the heat sink to

Management maximize life.

**Environment** Dry and damp rated in operating ambient

temperatures of 0-40°C (32-104F).

Individual for LED cluster in each louver cell. Louver

**LED** 

#### OPTICS







**SO** spotless lens

**L** Louver

**0.25G** Glo lens

#### **SPOTLESS LENS**

Frosted acrylic snap-in micro lens.

#### **PARABOLIC LOUVERS**

Die formed semi-specular aluminum (22 gauge).

#### **GLO LENS**

0.25" frosted acrylic drop lens. Patented design.

#### • SYSTEM (S#)

BEAM2 SQUARE linear systems, with the use of a strong profile, allow for a nearly hair thin connection system of continuous runs. Lengths of 4', 8', 12' as well as custom lengths are available. Runs of BEAM2 SQUARE that are greater than 12' in length are designated as systems (S#). This means that the run is comprised of a combination of 4', 8' and/or 12' sections to be assembled on site using our joining system. For more information on systems and joining, please refer to the BEAM installation sheets available for download at www.axislighting.com.

#### WARRANTY

Axis Lighting will warrant defective LEDs, boards, and drivers for 5 years from date of purchase. Warranty is valid if luminaire is installed and used according to specifications. If defective, Axis will send replacement boards or drivers at no cost along with detailed replacement instructions and instructions on how to return defective components to Axis.

© 2016 Axis Lighting Inc.

1.800.263.2947

[T] 514.948.6272








#### InstaJoiner

TWIN BEAM2 SurroundLite luminaires feature InstaJoiner, a unique, patent-pending joining system developed by Axis offering fast, single-screw tightening.

**NOTE:** Mount each system segment individually.


## Do not assemble system prior to mounting

Allow a minimum of 6" between end of long runs and wall.




#### SECTION VIEWS


# 0.25G 0.25" Glo lens



## L Louver



## SO Spotless lens








#### MOUNTING OPTIONS


## CT TILE CEILING - ON GRID






Power feed


## CA DRYWALL CEILING






Power feed

SA STEM MOUNT IN DRYWALL CEILING





Power feed

Non power feed

#### OTHER MOUNTING OPTIONS

BEAM2 SQUARE is also available as Surface or Wall Mount.

**1** Specification sheets and installation sheets for all mountings for BEAM2 SQUARE luminaires are available for download at www.axislighting.com.

#### MRII LED LAMPS

4

Blank Extruded aluminum (0.075" nominal)
MR11 LED 1.4" diameter

**Quantity** For every 4' section, there may be up

to a maximum of 4 x MR11 LED lamps. **Spacing**Each MR11 LED lamp is placed centered

on a blank section 6" in length.


For a series of MR11's within a given section length, they will be spaced evenly on a longer blank section.


The directed light of MR11 LED lamps  $2^{3}/4$ "


are fixed downward

are fixed downward.

Custom spacing may be available on special request.







**Beam Angle** 45 nominal degrees

Input Watts 3W Nominal Lumens 50 lumens

**Efficacy** 17 lumens per watt

Color Rendering Index (CRI) 80

**.ife** 25,000 hours at L<sub>70</sub>

**Correlated color temperature (CCT)** 2700K

• More options are available upon request. Please consult factory.






#### INTEGRATED CONTROLS

BEAM2 SQUARE luminaires allow the use of integrated controls such as daylight sensors (DS), occupancy sensors (OS) and combination daylight/occupancy sensors (DOS). These options can be seamlessly integrated into our luminaires. The control system could be used to optimize the lighting of the space by reducing energy consumption through daylight harvesting and occupancy, thereby improving the overall interior environment and allowing for LEED credits.

• Consult factory for other options.



#### The integrated control systems offered are:

#### • DAYLIGHT HARVESTING (DS):

With Daylight sensors, maximum lamp output is reduced according to the available amount of natural light. By reducing maximum lamp output, energy consumption is reduced by up to 20 percent in a process known as "Daylight Harvesting".



EC-DIR-WH, FD-301 Luxsense, Micro Luxsense

#### • OCCUPANCY (OS):

When a room is vacated, occupancy sensors ensure the light will be turned off after a programmed delay as well as ensuring that light remains on while the room is occupied.



FS-205, FS-355, FS-155 - Line Voltage FS-505, FS-505C

## DAYLIGHT HARVESTING AND OCCUPANCY (DOS):

ACTILUME, a combination of Daylight & Occupancy sensor from Philips, along with a 0-10V or DALI driver can be used in one form factor.



Actilume 1-10V Actilume DALI

## ● ENLIGHTED INTEGRAL (EN) / ENLIGHTED REMOTE (ENR):

A combination of Daylight, Occupancy & Temperature autonomously control illumination levels, monitor occupancy and environmental conditions. Data is transmitted wirelessly to the Enlighted networked management system.



#### INSTALLATION EXAMPLE

#### Sensor location option



\* Incorporating IC controls may affect the length of the luminaire. Please contact factory for more details.



#### • INTEGRATED CONTROL OPTIONS

SENSORS	BRAND	Model	ТУРЕ
	Lutron	EC-DIR-WH	Daylight, IR
	Wattstopper	FD-301	Daylight
Daylight Sensor (DS)	Philips	Luxsense, LR1220/00	Daylight
	Philips	Micro Luxsense	Daylight
	Wattstopper	LS-102	Light Saver (Ambient light level)
	Wattstopper	FS-205v2	PIR Occupancy & Ambient light level
	Wattstopper	FS-355 (need lenses)	PIR Occupancy & Ambient light level
	Wattstopper	FS-155	PIR Occupancy & Ambient light level
	Wattstopper	FS-505	Ultrasonic Occupancy (Staircase)
Occupancy Sensor (OS)	Wattstopper	FS-505C	Ultrasonic Occupancy (Open Area)
decupancy sensor (65)	Wattstopper	FM-105	High Frequency Occupancy (Wet)
	Lutron TriPak Wireless	LRF2-OCR2B-P-WH	PIR Occupancy
	Lutron	LOS-CDT	Ultrasonic Occupancy + PIR
	Lutron	LOS-CIR	PIR Occupancy
	Philips	Actilume, LR11655	Daylight & PIR Occupancy
D    1	Wattstopper	FS-305 (need Lenses)	PIR Occupancy
Daylight & Occupancy Sensors (DOS)	Wattstopper	FS-305 RC	PIR Occupancy & Ambient light level
3013013 (1003)	Creston	GLS Series	Daylight and/or PIR Occupancy
	Echoflex	MOS Series	Daylight and/or PIR Occupancy
Enlighted sensor (EN, ENR) Enlighted integral / remote		SU-3E-00	Daylight, Occupancy & Temperature






#### PHOTOMETRIC DATA

#### 1000 lm/ft



#### PHOTOMETRIC CURVE



Lumen/ft: 1000 lm/ft Total Lumens: 3854 lm (for 4ft)

Input Watts: 39.6 W Efficacy: 97 lm/W

IES FILE: B2SQDLED-0-1000-80-35-L-4.IES

TESTED ACCORDING TO IES LM-79-2008

80 CRI shown. To calculate watts and efficacy at 90 CRI, apply a multiplier of 0.8.

#### **CANDELA DISTRIBUTION**

	Horizontal Angles									
Vertical Angle	0	22.5	45	67.5	90					
0	2297	2297	2297	2297	2297					
5	2356	2348	2337	2321	2312					
15	2483	2504	2693	2915	2904					
25	2322	2513	3107	3055	2851					
35	1290	1752	2342	1633	1320					
45	194	307	658	478	428					
55	32	48	76	175	250					
65	6	8	13	17	20					
75	2	2	3	5	5					
85	0	I	ı	ı	I					
90	0	0	0	0	0					

## **ZONAL LUMENS**

	Lumens
Zone	
0	
0-10	228
10-20	768
20-30	1260
30-40	1073
40-50	397
50-60	106
60-70	19
70-80	4
80-90	ı
90	

#### LUMINANCE DATA (cd/m²)

	Horizontal Angles									
Vertical Angle	0	45	90							
45	4597	15642	10171							
55	949	2223	7334							
65	219	521	807							
75	110	208	312							
85	77	154	212							

