




REGOLO GENERAL WARNING




WARNING:

DO NOT ASSEMBLE CONTINUOUS RUN ON THE GROUND AND LIFT INTO PLACE.
JOINTS WILL DISTORT AND NOT CREATE A TIGHT FIT.
JOINING HARDWARE WILL HAVE TO BE PURCHASED AND REPLACED.



FOR PROPER INSTALL INFORMATION SEE
RESPECTIVE SERIES INSTALLATION INSTRUCTIONS.



10770 East 51st Ave, Denver, CO 80239 - Phone (303)287-9646 Fax (303)287-0316

Instructions and dimensions are subject to change without notification. Instruction sheets on our website supersede all other versions.

2016 Rev. A

REGOLO WALL

INSTALLATION INSTRUCTIONS - LED

⚠ WARNINGS



Risk of electrical shock or fire, disconnect power during installation or servicing. Read all instructions completely before starting installation. Install and wire in accordance to all national and local codes by a certified electrician. Fixture may be sharp, handle with care. Let fixture cool before maintenance.

⚠ AVERTISSEMENTS


Risque d'électrocution ou d'incendie. Déconnectez l'alimentation durant l'installation ou la maintenance. Lisez attentivement toutes les instructions avant de commencer toute installation. Faites installer et câbler selon les normes Nationales et Locales par un électricien certifié. Les installations peuvent être coupantes, à manipuler avec précaution. Laissez refroidir les installations avant une opération de maintenance.

⚠ ADVERTENCIA

Riesgo de descarga eléctrica o un incendio, desconecte la alimentación durante la instalación o servicio. Leer todas las instrucciones completas antes de empezar la instalación. Instalar y cablear en acuerdo a las reglas nacionales y códigos locales por un electricista certificado. El accesorio puede estar agudo, agarre con cuidado deje que el accesorio. Enfriar antes de mantenimiento.





OVERVIEW



MAINTENANCE




AVOID TOUCHING THE LED BOARDS.




If access to wire way is needed, remove the four screws from the LED reflector. To remove the reflector completely, separate the electrical disconnect. Store the reflector in a clean, safe place during installation or maintenance.

Optional specular asymmetric reflector. Remove two screws from the LED reflector to access the wire way. Joint cover brackets are not provided for this option.




WALL MOUNTING BRACKET LAYOUT


⚠ RUN CONFIGURATIONS ARE SPECIFIC TO FACTORY DRAWINGS. CONSULT SUBMITTAL BEFORE BEGINNING INSTALLATION. ⚠



PLAN VIEW OF WALL MOUNTING BRACKET



PLAN VIEW OF HOUSING BACK






ROW INSTALLATION - INDIVIDUAL INSTALLATION FOLLOW STEPS 1 THROUGH 4.




1




Remove the two wall mounting brackets from the back of the stand alone or starter luminaire.

2




Layout and install the wall mounting brackets. (Extra blocking, J-Box and hardware by others. Refer to PG-3 for bracket layout).

3




The stand alone or starter luminaire wall mounting brackets must be level before hanging the luminaire. Mount all wall brackets before continuing row installation.

4




Hang the luminaire, rotate over the two wall mounting brackets. Tighten the set screw to secure the luminaire.

5




Align the tabs with the extrusion slots. Make sure the power supply connectors snap together.

6




Joiner bracket is not symmetrical and must be installed in correct slots to work properly.

7




Arbitrary view from inside wall.


8



9



Secure by tightening the joiner bracket screw.



Install the joint cover brackets with provided #8X1/4" sheet metal screws.