

CAUTION: THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SAVE THESE INSTRUCTIONS!



WARNING: Before beginning installation, disconnect electrical power at main switch or circuit breaker.

## **IMPORTANT SAFEGUARDS**

Ensure that the electrical wiring conforms to the National Electrical Code NEC® and local regulations if applicable. Installation and servicing of this equipment should be performed by qualified service personnel only. Do not mount near gas or electric heaters. Equipment should be mounted in locations and at heights where it will not readily be subjected to tampering by unauthorized personnel. The use of accessory equipment not recommended by the manufacturer may cause an unsafe condition. Any modification or use of non-original components will void the warranty and product liability. Do not use this equipment for other than intended use.

## GENERAL INSTRUCTIONS

- Carefully unpack your new fixture and lay out all the parts on a clear area. Be careful not to lose any small parts necessary forinstallation.
- Remove the fixture lens, and remove the internal LED tray.
- Attach included cross bar to junction box (screws supplied by others).
- Assemble junction cover with threaded nut on inside, put pendant rod thru cover, and thread rod into cross bar until nut is tight and secure against cross bar. Use the included collar and set screw to secure cover.
- Place lower threaded end of rod thru
  the body of the luminaire, lower
  collar until flush with back of body
  (secure with lock screw), and tighten
  nut from inside of body until tight
  and secure.
- 6. Reassembly light unit.

