

# Brilliance LED 1156 SCB 12 Volt

2 Watt (replaces 20 watt halogen)



## Description:

The Brilliance SCB LED lamp is specifically designed for landscape lighting retrofit. The compact LED utilizes CREE's XT-E chipset and features Brilliance LED's multi-directional beam pattern which is energy efficient and water resistant making it ideal for pathway lighting fixtures.

## Specifications/Features:

- Engineered for landscape lighting fixtures
- 8-18 Volts AC/DC
- 130 Lumen
- Kelvin Temperature 3000K Warm White
- Kelvin Temperature 5700K Cool White
- CRI:83
- CREE Chipset
- 35000 hour lamp life
- Conformal coated PC board
- Water resistant
- 5-year warranty



**Part Number**      **BRI 1156 SCB WW**  
                             **BRI 1156 SCB CW**

Specifications subject to change without notice.

Copyright 2012 Brilliance LED  
7202 E Cave Creek Road, Carefree, Arizona 85377  
800-867-2108  
[www.brillianceled.com](http://www.brillianceled.com)

# Single Contact Bayonet (SCB) 1.5 watt-85 lumens



(replaces 15 watt halogen)

## Description:

The Dynasty® SCB LED lamp is designed specifically for landscape lighting retrofit. This compact LED utilizes CAO Group's patented high-flux LED which is energy efficient, water resistant, and features a multi-directional beam pattern, making it ideal for pathway lighting fixtures.

## Specifications/Features:

- Engineered for Landscape Lighting Fixtures
- 8-25 VOLTS AC/DC
- 85 Lumen
- Kelvin Temperature: 2700 Warm White
- CRI: 85
- Nichia Chipset
- 35,000 hour lamp life
- Conformal coated PC board
- Water Resistant
- Dimmable (with most magnetic transformers)
- Removable diode to change between colors
- 5-Year Warranty



**Part Number**      **SCB 1156 XX**

- ◇ WW = Warm White
- ◇ CW = Cool White
- RED = Red
- GREEN = Green
- BLUE = Blue
- AMBER = Amber

Color

Specifications subject to change without notice.

Copyright 2012 Brilliance LED  
7202 E Cave Creek Road, Carefree, Arizona 85377  
800-867-2108  
www.brillianceled.com